

A800 SMART Combo



Food & Beverage



Fashion & Retail



Supermarkets





Powered by Android 10



PCI PTS 6.x, SRED



Display



2MP Front 5MP Rear



Advanced Connectivity



SPECIFICATIONS

	O	DAVO: David Landarila
<u>o</u> o	Operating System	PAXBiz Powered by Android 10
	Processor	Application CPU: Quad-core Cortex-A53, 2GHz Security CPU: Security CPU 32-bit RISC-core ARM v7-M, 72MHz
	Memory	16GB eMMC + 2GB DDR 1 microSD Card Up to 128GB
	Card Readers	Chip & PIN NFC Contactless Magnetic Stripe
©	Cameras	2MP Front-Facing 5MP Rear-Facing
	Displays	5.7" Capacitive Touchscreen 720 x 1440 Pixels
	Comms Configurations	4G Wi-Fi® 2.4GHz & 5GHz Bluetooth®5.0 Optional: Ethernet via HUB
Ī	Battery	2300mAh 7.2V
	Printer	Paper Roll Outer Diameter: 40mm
SAM	SIM / SAM	1 Micro SIM + 2 SAM 2 Micro SIM + 1 SAM
戊 ゥ)	Audio	1 Audio Jack
	Ports	1 Type-C (OTG)
	Adapter	Input:100-240V AC, 50Hz/60Hz Output: 5.0V DC, 3.0A
	Physical	188 x 66 x 79mm, 467g (including battery)
Ğ	Environmental	-0°C ~ 50°C (32°F ~ 122°F) Operating Temperature -20°C ~ 70°C (-4°F ~ 158°F) Storage Temperature 10% ~ 93% Relative Humidity, Non-Condensing
(§)	Accessories	Optional: HUB (1 LAN, 3 USB) Charging Base
	Certifications	PCI PTS 6.x SRED EMV L1/L2 EMV CL L1 Mastercard contactless Visa payWave Amex D-PAS qUICS Interac Flash CE FCC IC UL 3C







This document is provided to you for informational purposes only. All features and specifications are subject to change without notice. microSD logo is a trademark of SD-3C LLC. The Bluetooth* word mark and logos are registered trademarks owned by Bluetooth SIG, Inc. and any use of such marks by PAX Technology, Inc. is under license. EMV* is a registered trademark in the U.S. and other countries and an unregistered trademark elsewhere. The EMV trademark is owned by EMVCo, LLC. Android* is a trademark of Google LLC. PAX, PAXBE*, PAXSTORE, and/or other PAX products referenced herein are either trademarks or registered trademarks of PAX Technology, Inc. or its Affiliates. Other trademarks and trade names are those of their respective owners. © 2022 PAX Technology, Inc. All rights reserved.

